

YSHIELD® BU3 | Canopy base | Double bed | HNG80

88 dB attenuation at 1 GHz. Width 260 cm, depth 260 cm. Including grounding components.




YSHIELD® BU3



YSHIELD® BUx



YSHIELD® HNG80



YSHIELD GmbH & Co. KG
Rotthofer Straße 1
94099 Ruhstorf, Germany
Further information:
www.yshield.com,
info@yshield.com

Properties

To achieve a full Faraday cage with a canopy, it is also necessary to shield from below. **This canopy base has a very high shielding attenuation, lies very flat and is delivered including the entire necessary grounding material.** Scope of delivery includes, among other things, grounding plug GP1 for schuko sockets E/F and the canopy connector GCMV for canopies (you can choose if you want to connect the canopy with a velcro or magnet).

This canopy base consists of **three panels that are placed with an overlapping of 5 cm, made of the material HNG80 with 80 dB shielding attenuation.** Small metal plates are pre-assembled at one end of each panel - grounding will be screwed onto them. If you choose this canopy base, we highly recommend **covering it completely with a fabric or carpet.** This cover will also hide the 4 mm high electrical connectors and cables behind the bed.

Technical data

- **Attenuation: 88 dB**
- **Size: Width 260 cm, length 260 cm, sheet thickness 0.1 mm**
- **Materials: Polyester, copper, nickel, aluminium**
- **Scope of supply: 3 panels HNG80 to each 260 cm, 1 Grounding plug GP1 (Schuko E/F), 1 Grounding connector magnet/hookloop GCMV, 3 cables GL85 (85 cm), 1 cable GL500 (500 cm), all necessary screws, discs, dowels, cable lugs and a screwing tool with Torx®-Bits. No room decoration in the scope of delivery.**

Care instructions

HNG80 can neither be washed nor cleaned

Grounding

This product with an electrically conductive surface **has to be integrated into the functional-equipotential bonding (FEB).** Please find suitable grounding accessories under "Grounding".

Shielding attenuation HF & LF

This product **shields high frequency electromagnetic fields (HF).** Unless otherwise stated, the indicated dB-values apply to 1 GHz. Measurement from 600 MHz to 40 GHz according to standards ASTM D4935-10 or IEEE Std 299-2006.

This product with an electrically conductive surface **shields low-frequency alternating electric fields (LF).**

Installation instructions

- Lay the two or three panels **(1)** out with an overlapping of approx. 5 cm - connecting plates all need to be laid on the same side with the stepped side facing upwards.
- Connect the two or three panels **(1)** with the 85 cm long cables GL85 **(4)**. Use the black tensions discs when screwing the cable lugs tight.
- Connect the canopy connector **(3)** with the 85 cm long cable GL85 **(4)**. Use the black tensions discs when screwing the cable lugs tight.
- Connect the grounding plug **(2)** with the 5 m long cable GL500 **(5)**. Use the black tensions discs when screwing the cable lugs tight.
- Connect the canopy connector **(3)** with the canopy, either with the magnetic plate or velcro.
- The electrician must install the grounding plug **(2)** tightly in the socket outlet.

